

## Item Number 0110000

## Saf-T-Brace®

For Retrofit or New Construction Applications

No Attic Access Required

### Specifications

- Provides fast fingertip expansion and positive attachment to joists
- Teeth twist and lock into joist to create more secure connection
- Magnet secures box to hanger bar for hands-free installation
- Fits 16" to 24" ceiling joists
- Fits all ceiling fans
- For Fixture support of 150 lbs. or less on 16" centers
- For Fixture support of 70 lbs. or less on 24" centers
- Acceptable for fan support of 70 lbs. or less
- Position box anywhere along the brace
- Heavy duty, all metal, dual mount\* electrical box
- 1-1/2" box depth, 15.5 cubic inch wiring capacity
- Six 1/2" Romex® or conduit knockouts; 1 Romex® connector
- Includes Saf-T-Cap® to protect inner workings during drywall installation
- Includes mounting hardware and instructions



### Pack Information

- Individually Packaged
- 24 Per Cut Case



Meets or Exceeds UL Standards Regarding Exposed Threads Within Box. Meets or Exceeds NEC® Safety Codes.

\* Dual Mount = Box is threaded for #8-32 (ideal for box covers and lightweight fixtures) and #10-24 screws (ideal for heavier fixtures and ceiling fans).

Romex® is a registered trademark of Southwire Company.

*Specifications are subject to change without notice, please visit [www.westinghouselighting.com](http://www.westinghouselighting.com) for latest information.*

®, WESTINGHOUSE, and INNOVATION YOU CAN BE SURE OF are trademarks of Westinghouse Electric Corporation. Used under license by Westinghouse Lighting. All Rights Reserved.